
PCB Power Relay

Miniature High Capacity Relays with SPST-NO 10A and SPST-NO + **SPST-NC 8A**



- Small High-capacity Relays Compact: $20 \times 15 \times 10$ mm (L \times W \times H).
- Low power consumption: 200 mW.
- Ultrasonically cleanable models is available.
- Exclusive P6C model for sockets is now available.

RoHS Compliant



Ideal for output applications of control equipments





R1 (1) (2)

■Model Number Legend

G6C-	□ -						-	-]-		-[
	_	_	_	_	_	_	_	_	-	_		_	
	1	2	3	4	5	6	7	8	3	9		10	

1. Relay Function

None: Single-side stable U: Single-winding latching

K : Double-winding latching

2. Number of poles

1: 1-pole/SPST-NO (1a)

2: 2-pole/SPST-NO (1a) + SPST-NC (1b)

3. Contact Form

1: SPST-NO (1a)

4. Contact Type

1: Single

5. Enclosure rating

4: Fully sealed

7: Flux protection

6. Terminal Shape

P: PCB terminals

Socket mounting Terminals

7. Contact Material

None: Standard (Ag-alloy (Cd free))

FD: AgSnIn Contacts (Suitable for DC inductive load with high inrush current)

8. Approved Standards

US: UL/CSA

9. Washability

None: Standard model (not compatible with ultrasonically cleanable models)

: For ultrasonically cleanable

10. Mounting

None: Mounted directly to

PCB

P6C: Mounted to Socket

■Ordering Information

●Standard Models (UL, CSA certified)

	Relay Function	Single-side stable		Single-winding late	hing	Double-winding latching		Minimun
Enclosure rating	Contact form	Model	Rated coil voltage	Model	Rated coil voltage	Model	Rated coil voltage	packing unit
		G6C-1117P-US	3 VDC	G6CU-1117P-US	3 VDC	G6CK-1117P-US	3 VDC	100 pcs/
	SPST-NO (1a)		5 VDC		5 VDC		5 VDC	
			6 VDC		-		6 VDC	
			12 VDC		12 VDC		12 VDC	
Elux protection			24 VDC		24 VDC		24 VDC	
Flux protection			3 VDC		3 VDC	G6CK-2117P-US	3 VDC	tray
	SPST-NO	G6C-2117P-US	5 VDC	G6CU-2117P-US	5 VDC		5 VDC	
	(1a) + SPST-NC (1b)		6 VDC		6 VDC		6 VDC	
			12 VDC		12 VDC		12 VDC	
	, ,		24 VDC		24 VDC		24 VDC	
		G6C-1114P-US	3 VDC	G6CU-1114P-US	3 VDC	G6CK-1114P-US	3 VDC	
	SPST-NO (1a) SPST-NO (1a) + SPST-NC (1b)		5 VDC		5 VDC		5 VDC	
			6 VDC		6 VDC		6 VDC	
			12 VDC		12 VDC		12 VDC	
Fully seeded			24 VDC		24 VDC		24 VDC	100 pcs/
Fully sealed -		GEC-2114D-US	3 VDC	G6CU-2114P-US	3 VDC	G6CK-2114P-US	3 VDC	tray
			5 VDC		5 VDC		5 VDC	
			6 VDC		6 VDC		6 VDC	
			12 VDC		12 VDC		12 VDC	
	,		24 VDC		24 VDC	•	24 VDC	

Note. Products with UL/CSA certification marks will be supplied for orders of standard models (-US models).

OMRON G6C-1117	
-US	CONTACT:
	TV-5
24VDC	10A 250VAC
MADE IN	10A 30VDC
JAPAN	COIL:24VDC

OMRON G6C-2114F	
-US	CONTACT:
24VDC MADE IN JAPAN	TV-5 8A 250VAC 8A 30VDC COIL:24VDC

OUItrasonically Cleanable Models (UL, CSA certified)

	Relay Function	Single-side stable		Single-winding latching		Double-winding latching		Minimun	
Enclosure rating	Contact form	Model	Rated coil voltage	Model	Rated coil voltage	Model	Rated coil voltage	packing unit	
			3 VDC	G6CU-1114P-US	-	G6CK-1114P-US	-		
	ODOTNO	G6C-1114P-US-U	5 VDC		5 VDC		5 VDC	100 pcs/	
	SPST-NO (1a)		6 VDC		-		_		
			12 VDC		12 VDC		12 VDC		
Fully sealed			24 VDC		-		24 VDC		
Fully Sealed		-	-		-		-	tray	
	SPST-NO		5 VDC		-		5 VDC		
(1a) + SPST-NC	(3h(2114P-U5-U	_	G6CU-2114P-US	-	G6CK-2114P-US	-			
	(1b)		12 VDC		-		12 VDC		
	, ,		24 VDC		-		_		

Note. Products with UL/CSA certification marks will be supplied for orders of standard models (-US models).

OMRON G6C-1117 -US	P PL () CONTACT:
24VDC MADE IN JAPAN	TV-5 10A 250VAC 10A 30VDC COIL:24VDC

OMRON
G6C-2114P
-US
TV-5
24VDC
8A 250VAC
MADE IN
8A 30VDC
JAPAN
COIL:24VDC

Connecting Sockets (Sold Separately)

Applicable relays	Model	Minimun packing unit		
G6C-2114P-US-P6C G6C-2117P-US-P6C G6C-1114P-US-P6C G6C-1117P-US-P6C G6CU-2114P-US-P6C G6CU-2117P-US-P6C G6CU-1114P-US-P6C G6CU-1117P-US-P6C	P6C-06P	20 pcs/tube		
G6CK-2114P-US-P6C G6CK-2117P-US-P6C G6CK-1114P-US-P6C G6CK-1117P-US-P6C	P6C-08P			
Removal Tool	P6B-Y1			
Hold-down Clips	P6B-C2	1		

Note 1. Use the G6C-□□□□P-US-P6C to mount to a P6C Socket.

^{2.} When using by combining sockets, the rated current will be 5A due to its rated switching current.